

## 8. TRANSMIT TIME LIMITER (TTL) TIME SETTING

The KG107 incorporates a TTL circuit. The TTL inhibits continuous transmission for more than the specified time and shifts the radio to receive operation automatically. As soon as the TTL time period is exceeded, an alert tone of 2kHz is heard from the speaker and remains audible as long as the PTT switch is depressed.

The TTL time period is adjustable by rearranging the Jumper Switch located on the PCB in the control head according to switch arrangement chart below.

TIME PERIOD	SWITCH #1	SWITCH #2
No Time Limit	ON	ON
30 SECS	OFF	ON
60 SECS	ON	OFF
90 SECS	OFF	OFF

<http://www.geocities.com/airwavesau/>